




Manual 777	
<b>1</b>	<b>Multi-function Unipolar Tester for Electric Installations</b>
<b>2</b>	<p><b>General description</b></p> <p>FAZER 767 BASIC is intended for performing basic tests of 220V/380V electric installations, car installations and other electric installations. With Fazer 767 you can also check the operations of electrical devices. As for electronics, Fazer 767 allows, among other things, to detect 0/1 and check resistors, capacitors, diodes and transistors for malfunction. The device does not have a power off switch. Fazer consumes power only during the measurement. Precise, carefully developed Fazer's electronic circuitry ensures very low power consumption. Alkaline batteries LR44 allow to perform more than 10000 measurements. Fazer cannot be dismantled.</p>
<b>3</b>	<p><b>Rules for correct disposal of used equipment</b></p>  <p>1. The sign shown to left means that you should not place used equipment in a trash bin, together with usual home and commercial waste products.</p> <p>2. Elements used to manufacture this device should be recycled under the system of selective collection of electric and electronics equipment (in accordance with the Directive WEEE2002/96/WE).</p> <p>3. To dispose of used equipment you should return it to the vendor or deliver to the electric equipment collection point. Device's weight &lt;40g.</p>
<b>4</b>	<p><b>Sales package:</b></p> <p>FAZER 767 BASIC with batteries, a detailed user manual with applications, disposable packaging.</p>
<b>5</b>	<p><b>Correct operations</b></p> <ul style="list-style-type: none"> <li>- protect the device against humidity higher than 90% and the temperature above 60°C;</li> <li>- do not hit the device against hard objects and do not separate elements of the device's housing;</li> <li>- do not the measurement pint as a lever;</li> <li>- the hardened screwdriver is intended for screws not thicker than 4 mm.</li> </ul>
<b>6</b>	<p><b>24 months warranty</b></p> <p>The manufacturer guarantees failure-free operations of the device. The warranty is valid for 24 months from the purchase date and for 30 months from the production date. The manufacturer's warranty shall only be respected if the device is used in accordance with correct operation recommendations. The warranty does not cover batteries and effects of the battery damage. (Purchase date, stamp and signature of the seller)</p>
<b>7</b>	<p><b>Declaration of Conformity</b></p> <p>Fazer 767 is classified in PKWiU (Polish Classification of Products and Services) under the number 33.20.43-59.00.</p> <p>Fazer 767 has been designed in accordance with the standard PN-EN 6101-1 and complies with the provisions of the Directive 73/23/EEC dated 19 February 1972 as amended by 93/68/EEC. This Directive applies to safety of devices up to 1,000V.</p>

8	<b>Basic modes of operations</b> Fazer 767 operates in one of the four basic modes: PHASE, CONT, VOLT. In the PHASE mode, Fazer 767 uses the operator's body as electric earth, and in the CONT and VOLT modes Fazer 767 uses the skin's conduction. Thus, good contact between a hand and the contact is advisable. In order to improve this contact you can slightly moisten your fingers before performing a measurement in the CONT and VOLT modes.	
9	<b>"PHASE" Mode</b> 	<b>do not touch the contacts, do not touch any contacts</b> <b>ALTERNATING VOLTAGE PHASE INDICATOR</b> Grab the Fazer's body. Do not touch the metal contacts.. Voltage "PHASE" will be indicated by a red LED (visual signal) Note: Sometimes Fazer may indicate voltage in case of a non-live wire but one that is located near another live wire.
10	<b>"CONT" Mode</b> 	<b>touch the "CONT" contact</b> <b>CONDUCTION CONTINUITY INDICATOR.</b> FAZER 767 differentiates between non-conduction and conduction at approx 1 MΩ. Press the CONT contact. The measurement pin and the operator's second hand should touch measurement points of a tested object. Conduction is signalled by the red LED going ON. Note: In the CONT mode the measurement should be performed with the power supply switched OFF, since induced voltage makes correct indication impossible.
11	<b>"VOLT" Mode</b> 	<b>touch the "VOLT" contact</b> <b>"-" DIRECT VOLTAGE INDICATOR.</b> Fazer detects voltage and polarization of direct voltage with the value bigger than 2.5 V. Press the VOLT contact. The measurement pin indicates positive voltage in relation to the VOLT contact. Therefore, the operator's second hand should be connected to the voltage negative pole. For instance, the battery's or power supply plug's "-" contact, or the body of a device, where one can find negative ground. If there is "+" voltage on the pin, Fazer will react by lighting up the visual indicator.
12	<b>Exchanging the batteries</b> 	Power supply: two alkaline batteries LR44, AS44 or replacements. Batteries are located under a cover on the Fazer's bottom side. Pull the battery cover aside gently. Slide the cover towards the measurement pin. Replace the batteries. Observe the correct "+" and "-" polarization. Follow the marks inside the battery chamber.
	<b>Battery maintenance</b> If the device fails to signal the measurement results the batteries' contacts may be dirty. Take the batteries out, clean them with a dry cloth or spirit and put them back in. Sometimes, it's enough just to move the batteries around their axis inside the device.	
13	<b>The most frequent applications</b>	
	220/380V grid, electric installations, devices, electronics, direct current, cars	
14	 <b>Detection of PHASE in the PHASE mode</b>	
	Phase and zero detection is a basic test, equivalent to operations of the so called neon tester, the only difference being that in case of Fazer there is no need to touch a metal contact. Fazer should be held by its body. Touch a tested area with the pin. Fazer will react when it detects 220V voltage phase. Fazer will not react in case of "zero". One should note the voltage induced on wires connected neither to "zero" nor "phase" but running alongside live wires.	

15		<b>Breaks/shortings detection. Testing cables. The CONT mode</b>
<p>This application allows to control cables, fuses, light bulbs, etc. for current conduction. Touch one of the ends of a tested object with the measurement pin and grab the other end of the object with you hand. If there is a break in conduction FAZER will not react. A long cable ruptured inside its insulation - drive a metal pin inside the cable at a certain distance from one its ends and check for conduction. By moving the pin you can find the rupture location.</p>		
16		<b>Determining the sequence of wires in a group of conductors - the CONT mode</b>
<p>This application allows to identify wires in large groups of conductors. Example: determining of the sequence of wires is necessary e.g. when we have two cable boxes (A and B) with several wires of repeated colours coming out of them.</p> <ul style="list-style-type: none"> <li>- take a wire with unique colour in box A and B as the point of reference;</li> <li>- in the box A, attach any wire to the wire of reference and try to detect it in the box B with the CONT test, and then assign a sequential number to it (here, 2);</li> <li>- repeat it with remaining wires.</li> </ul>		
17		<b>Verification of earthing - the PHASE mode</b>
<p>With this application you can roughly determine the quality of earthing of home devices connected to 220 V grid. If a metal housing of a washing machine, a refrigerator, etc. is properly earthed, then FAZER will not react in the PHASE mode. If FAZER reacts it means that the device's earth may not be enough, which may lead to electric shock. FAZER's positive reaction will not always indicate danger (induced fields). However, no reaction confirms correct earthing.</p>		
18		<b>Working/Malfunction test. Searching for a rupture. The CONT mode.</b>
<p>With this application you can find a damage location in electric devices. Grab one of the pins of the power cable's plug with one hand and touch the plug's other pin with the Fazer's measurement pin in order to check for the continuity of conduction. You can locate a break inside the device by successively checking assembly points with the Fazer's measurement pin outwards. Note: there must not be 220V voltage nearby since it will disrupt the test.</p>		
19		<b>0/1 detection in digital circuits in the VOLT mode</b>
<p>When operating in the VOLT mode, Fazer has the ability to find "0" or "1" in digital circuits. The Fazer's activation threshold in the VOLT mode is approx. 1.5 V. Touch the assembly board (power supply zero) with your second hand. Fazer's measurement pin will detect gate bias (0/1).</p>		
20		<b>DC voltage detection - identification of "+" and "-" in the VOLT mode</b>
<p>This application allows to detect direct voltage levels from 2.5 V to 60 V. Grab the power supply's "-" of a tested device with one hand. Using Fazer's measurement pin you can search for places with positive direct voltage. Pole identification is done by changing the electrodes grabbed with the hand (or places on the device). General rule: Fazer will react if there is positive voltage (<math>U &gt; 2.5V</math>) on the measurement pint as compared with the operator's second hand holding the power supply's "-".</p>		
21		<b>Detection of +12V/ground in cars in the VOLT mode</b>
<p>Grab a non-painted element of the car's ground (negative ground) with your hand. In the VOLT mode Fazer will indicate points with +12V voltage. Note: with high level of air humidity you do not need to touch the car's body.</p>		

22	<b>Testing commutator motors in the CONT mode</b>
	Using the CONT mode you can check the continuity of individual windings in a motor. Touch ends of a single circuit with the measurement pin and the operator's second hand, equipped with a sharp-ended pin. If the motor's winding is in good order, Fazer will react
24	 <b>Testing of electronic components in the CONT mode</b>
	<p>Diodes and transistors: With Fazer 777 you can check the diode connection. For example an npn transistor. Grab the transistor's base with you fingers. Put Fazer's measurement pin to the transistor's collector and then to its emitter. Fazer will react.</p> <p>Resistors: You can check the continuity of conduction.</p> <p>Capacitors: Grab one of the capacitor's terminals with one hand and touch the other terminal with the measurement pin. Fazer will charge the capacitor, which will be manifested by a short flash. Changing the terminals will again cause a short flash.</p>
25	 <b>Telephone applications in the CONT and VOLT modes (touch CONT or VOLT)</b>
	All applications of the CONT and VOLT modes in 220V/380V electric installations and devices have their equivalents in telephone installations and devices. With the CONT mode it is easy to check the continuity of conduction in case of telephone set's elements (e.g. bells) and cables. Identification of wires in cable boxes becomes just as easy. The VOLT mode allows, among other things, to quickly determine the line's polarization.
26	 <b>Testing of fuses, light bulbs, etc. The CONT mode</b>
	Touch one of the fuse's terminals with one hand. Touch the other terminal with the measurement pin. If a fuse, light bulb, etc. are in working order, Fazer will react.